# **Ellawig companys** ladyshairextensions.com

# AC200-240V 50/60Hz Beam Moving Head Light 10 Watt LED Source

## **Basic Information**

. Place of Origin: 00 2 . Brand Name: 3 · Certification: Model Number: AQ9088 • Minimum Order Quantity: 100 Packaging Details: 付款方式 . Delivery Time: 供 能力 • Payment Terms: 期限 Supply Ability: 常 包装



# **Product Specification**

Features: Dimmable -20 ~ +40 • Operating Temp(): 25W • Power: IP20 • IP Rating:

Track Lights • Item Type: • Installation: 3 Phase LED . Light Source: Metal: Type Iron 203\*193\*15cm • Thickness: Box Type: Self Erecting Boxes 840~1300MW Radiation Power:

Metal Type:

Universal Type: Fit For 80% Model Cars' Injectors

Indian Hair: Yes

Size: 390x240x185cm

### **Product Description**

#### AC200-240V 50/60Hz Beam Moving Head Light 10 Watt LED Source

#### **Product Description:**

1. Lamp: NEOLUX 14R 295W

Channel mode: 18 DMX512 Channel
Pan scan: 540°(16bit) Electric correction
Tilt scan: 270° (16bit) Electric correction

5. Amazing dot matrix, four tact switch, 180°turning show 6. Color wheel: 14colors + white, and seven color effect

7. Power Input: 100-240V, 50/60Hz 8. Power Dissipation: 400W

9. IP level :IP20

#### **Quick Details:**

Brand Name	shangbulight
Emitting Color	RGBW
Application	Stage, Concert, Hotel, Stadium, etc.
Light Source	LED
Warranty(Year)	1-Year
Beam Angle	Parallel beam Angle 0°~3.8°
Strobe:	1-10 times/sec
Prism	independent 8 prism
Dimmer	linear dimmer
Channels	16/20 channel
Display	LCD color display
LCD color display	DMX512, self-walking, voice control, scene, master-slave mode

#### Features:

- 1. Full 360° bidirectional animation wheel
- 2. Separate color & gobo wheels
- 3. Manual focus
- 4. 3 Operational Modes: DMX, Sound Active, and Internal Show control modes
- 5. 2 DMX channel modes: 9 and 11 channel modes
- 4 built-in shows
- 7. 4-facet and linear rotating prisms and 2 frost filters
- 8. Gobo scroll mode

#### Specifications:

- 1. Power: 230W
- 2. Lamp: 230W beam lights bulb
- 3. Input Voltage(V):AC200-240V 50/60Hz
- 4. Dmx 512 channel: 16ch
- 5. Dimmer: Smooth dimmer from 0-100%
- 6. Focus:Can be controled through DMX with three different





Ellawig companys



+86-15399918960



service@ellawigss.com



ladyshairextensions.com