

## Club Event Decoration Moving Head Stage Light Powder 2800LM Plastic

### Our Product Introduction

#### Basic Information

- Place of Origin: 00
- Brand Name: 2
- Certification: 3
- Model Number: AQ9088
- Minimum Order Quantity: 100
- Packaging Details: 付款方式
- Delivery Time: 供 能力
- Payment Terms: 期限
- Supply Ability: 常 包装



#### Product Specification

- Features: 10W LED Source
- Housing Color: Black
- Power: 30W
- IP Rating: IP33
- Item Type: Track Lights
- Installation: 3 Phase
- Light Source: LED
- Metal: Type Iron
- Thickness: 203\*193\*15cm
- Box Type: Self Erecting Boxes
- Radiation Power: 840~1300MW
- Metal Type: Iron
- Universal Type: Fit For 80% Model Cars' Injectors
- Indian Hair: Yes
- Indian Hair: Yes

## Product Description

### Club Event Decoration Moving Head Stage Light Powder 2800LM Plastic

#### Product Description:

1. Equipped with a cold white 90 W COB LED
2. Positioning within 540° PAN and 200° TILT
3. Exact positioning via 16-bit PAN/TILT movement resolution
4. Auto, music, master/slave and DMX mode
5. Rotating 8-facet prism with variable speed
6. Strobe effect with 2-20 flashes per second
7. Built-in programs
8. Electronic dimmer (0-100%)
9. Motorized focus
10. Frost filter

#### Quick Details:

Product Name	BJ Adjustable Zoomable Dimmable Led Track Light	
Model	BJ-TR8026-C	BJ-TR9426-C
Power	25w/30w/35w/40w	25w/30w
Light Source	COB	
Certification	CE/RCM	
Beam angle(±5%)	20° - 60°	
Brightness Adjustable	10% - 100%	
Adjustable Angle	vertical adjust 90°+ level adjust 350°	

#### Features:

1. Automatic position correction
2. Supports QuickDMX - the wireless DMX system from Eurolite
3. Built-in phantom-powered USB port for QuickDMX, CRMX and WDMX receivers (optional)
4. Control panel with LC display for easy configuration
5. Mains input and output for power linking up to 8 units
6. LED: 1 x COB (chip-on-board) 90 W cold white (CW)
7. Color wheel 7 dichroic filters plus open
- Rainbow effect with adjustable speed in both directions
8. Gobo wheel with static gobos, 13 gobos und open shake effect
9. Can be operated in 14 CH mode

#### Specifications:

1. Power: 230W
2. Lamp: 230W beam lights bulb
3. Input Voltage(V):AC200-240V 50/60Hz
4. Dmx 512 channel: 16ch
5. Dimmer: Smooth dimmer from 0-100%
6. Focus:Can be controled through DMX with three different



**Ellawig companys**



+86-15399918960



service@ellawigss.com



ladyshairextensions.com

Room 501, unit 6, building 20, North Lane, east flower market, Beijing